



2.4 GHz Power Divider

PD2-2.4(T)

Description

These power dividers allow more than one antenna to be connected to a radio to help shape RF signals for your wireless networks. Signal loss from the dividers need to be considered when added to your wireless access points. See our electrical specifications below for more details.

ELECTRICAL

| Model | PD2-2.4 |
|---------------------|-------------------|
| FREQUENCY | 2350 MHz—2550 MHz |
| SPLITTING LOSS | 3.1 dB |
| INSERTION LOSS | 0.1 dB |
| TERMINAL TYPE | “N” FEMALE |
| MAXIMUM INPUT POWER | 300 WATTS |

MECHANICAL

| | |
|---------------------------|---|
| SIZE (inches) (L x W x H) | 6.625 (16.8 cm) x 3.375 (8.6 cm) x 2.125 (5.4 cm) |
| WEIGHT | 1.1 LBS (0.5 KG) |
| MATERIAL | ZINC PLATED STEEL |

Wade Antenna, Inc.

29 Sharp Road
Brantford, Ontario, N3T 5L8 Canada
Tel: 519.756.7157
Fax: 519.756.5056

(800) 463.1607
sales@wadeantenna.com
www.wadeantenna.com